METAL CASED CHARGER / STARTERS

TradeCharge30
RCBT30
30amp, 12/24V Bench Charger
150 amp Engine Start

TradeCharge35
RCBT35
35amp, 12/24V Bench Charger
180 amp Engine Start





Features

Charging Current (eff)	30 Amps	35 Amps
Starting Current (eff)	150 Amps	180 Amps
Outputs for 12V & 24V batteries	✔	✔
Charge rate display	Analogue	Analogue
Fully Insulated Clamps	✔	✔
Charge Rate Settings	2	2

Specification

AC Input Voltage	230V	230V
AC Input Power	650/1200W	800/1400W
Charge current (peak)	42A	50A
Charge current (effective RMS)	30A	35A
Charge current (arithmetic/EN)	20A	25A
Start current (peak)	180A	240A
Start current (effective RMS)	150A	180A
Start current (arithmetic/EN)	100A	120A
Cranking ON cycle (sec)	5	5
Cranking Off cycle (sec)	30	30
Cranking cycles (max)	5	5
Battery Capacity	30-300Ah	50-400Ah
Output fuse	Thermal	1 x 50A
Dimension(mm)	214x308x245	220x335x260
Weight (Kg)	11	14